


# Product data sheet

## eNet Standard radio centre plate




---

**Reference number**


---

**FM A 1700 WW**
**eNet Standard radio centre plate**

for inserts "blinds" ref.-no.: 1730 JE and 1731 JE

for inserts "light" ref.-no.: 1701 SE, 1704 ESE, 1702 SE, 1710 DE, 1711 DE, 1713 DSTE, 1723 NE

**Intended use**

- Manual, radio-controlled and time-controlled operation of e.g. blinds, shutters, awnings, lighting or fans
- Transmitter for radio communication of switching, dimming and blind commands
- Operation with switch, dimmer or blinds insert or satellite insert 3-wire

**Product characteristics**

- Status feedback to radio transmitter
- Status indication with LED
- Night mode
- Evaluation of satellite inputs

Functions in combination with blinds insert

- Positioning of the blind/shutter via scene request
- Position for sun protection and twilight
- Running time and ventilation position of the blind/shutter can be saved

Functions in combination with light insert

- Scene operation possible
- Switch-on brightness can be saved permanently when combined with flush-mounted inserts for dimming

Functions in combination with relay switch insert 2-channel

- Output a2 switches depending on output a1 e.g. to switch on ventilation, depending on the lighting, and switch it off with a delay.
- Switch-on delay of output a2 adjustable
- Run-on time of output a2 adjustable

Can be set with eNet server from version 2.2 (depending on insert):

- Repeater function
  - Slat change-over time/fabric-stretching time
  - Change-over time for direction change
  - Running direction invertible
  - Operating locks
  - Deactivating extension evaluation
  - Position for sun protection, twilight, lock-out protection and wind alarm
  - Maximum brightness
  - Minimum brightness
  - Dimming speed
  - Switch-on delay / switch-off delay
-

- Dim up/dim down ramp
- Switch-off warning
- Continuous on, Continuous off
- Hotel function
- Run-on time
- Light control

In order to use the eNet Standard radio centre plate, the eNet Server has to have at least version 2.3.

Supplementary functions with eNet server:

- Fully-encrypted radio transmission (AES-CCM)
- Update of the device software
- Reading of error memory

**Duroplastic (scratch-proof) glossy**

**Colour:**  
white

**Material:**  
duroplastic

