

eNet

eNet radio signal quality meter

Not suitable for encrypted radio transmission.

Only with eNet server software up to version 1.4.

#### Product characteristics

- Display of the signal quality of a selected eNet device using LEDs
- Display of the signal quality of status messages using LEDs
- Display of radio signals of non-eNet radio transmitters in the 868.0 ... 868.6 MHz frequency band using LEDs
- Switch-on, switch-off of the repeater functions of network-operated actuators, transmitters and energy sensors
- Battery operation with one included lithium button cell (CR 2450N)
- Devices switches off after 5 minutes without actuation

#### Technical data

Rated voltage: DC 3 V

Battery type: 1 x lithium CR 2450N (included)

Ambient temperature: -5 ... +45 °C

Radio frequency: 868.0 ... 868.6 MHz

Transmission range in free field: max. 100 m

Transmitting power: max. 20 mW

Receiver category: 2

Manufacturer: JUNG

Ref.-no.: FM DT