

eNet

eNet radio IP gateway

Only with eNet server software up to version 1.4.

Intended use

- Gateway for the operation of eNet switching, dimming and blind actuators via tablet PC or smartphone
- Operation with USB power supply
- Operation with WiFi router or access point, which support DHCP (Dynamic Host Configuration Protocol), or with static IP address
- Operation indoors

Product characteristics

- Up to 5 tablet PCs or smartphones can be simultaneously connected to the gateway
- Status LED to display the state of operation
- 20 lists for the compilation of favourite functions
- 24 channels for the operation of eNet actuators
- 16 scenes
- Update of the device software via tablet PC or smartphone
- Wall bracket

Function dependent on the app used:

- All On and All Off
- Lock-out protection for shutters or blinds
- Restraint function
- Master dimming function

Supplementary functions with eNet server:

- Operating locks
- Repeater function
- Reading of error memory

Technical data

Rated voltage: DC 5 V

Current consumption: typical 150 mA

Ambient temperature: 0 ... +45 °C

Dimensions (L x W x H): 80 x 76 x 25.5 mm

Connection USB: micro socket

LAN: RJ45 socket 8-pin

Radio frequency: 868.0 ... 868.6 MHz

Transmitting power: max. 20 mW

Transmission range in free field: typical 100 m

Receiver category: 2

Manufacturer: JUNG

Ref.-no.: FM-GATE-IP